



IECEx Certificate of Conformity

INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification System for Explosive Atmospheres

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.:	IECEx BAS 19.0018X	Page 1 of 4	<u>Certificate history:</u>
Status:	Current	Issue No: 5	Issue 4 (2021-03-15)
Date of Issue:	2022-11-08		Issue 3 (2020-11-12)
Applicant:	Eaton Electric Limited Great Marlings Butterfield Luton Bedfordshire LU2 8DL United Kingdom		Issue 2 (2020-02-12)
Equipment:	MTL SUM5 Universal Isolator		Issue 1 (2019-08-30)
Optional accessory:			Issue 0 (2019-06-20)
Type of Protection:	Intrinsic Safety		
Marking:	[Ex ia Ga] IIC (-40°C ≤ Ta ≤ +70°C) [Ex ia Da] IIIC (-40°C ≤ Ta ≤ +70°C) [Ex ia Ma] I (-40°C ≤ Ta ≤ +70°C)		

Approved for issue on behalf of the IECEx
Certification Body:

R S Sinclair

Position:

Technical Manager

Signature:
(for printed version)

pp D. Brearley

Date:
(for printed version)

8/11/2022

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting www.iecex.com or use of this QR Code.



Certificate issued by:

SGS Baseefa Limited
Rockhead Business Park
Staden Lane
Buxton, Derbyshire, SK17 9RZ
United Kingdom





IECEX Certificate of Conformity

Certificate No.: **IECEX BAS 19.0018X**

Page 2 of 4

Date of issue: 2022-11-08

Issue No: 5

Manufacturer: **Eaton Electric Limited**
Great Marlings
Butterfield
Luton
Bedfordshire
LU2 8DL
United Kingdom

Manufacturing locations: **MTL Instruments Pvt Limited**
No 3 Old Mahabalipuram Road
Sholinganallur
Chennai 600119
India

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended

STANDARDS :

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards

IEC 60079-0:2017 Explosive atmospheres - Part 0: Equipment - General requirements
Edition:7.0

IEC 60079-11:2011 Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"
Edition:6.0

This Certificate **does not** indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in:

Test Reports:

[GB/BAS/ExTR19.0047/00](#)
[GB/BAS/ExTR20.0159/00](#)

[GB/BAS/ExTR19.0192/00](#)
[GB/BAS/ExTR21.0027/00](#)

[GB/BAS/ExTR19.0345/00](#)
[GB/BAS/ExTR22.0187/00](#)

Quality Assessment Reports:

[GB/BAS/QAR06.0022/10](#)

[GB/BAS/QAR07.0017/09](#)



IECEx Certificate of Conformity

Certificate No.: **IECEx BAS 19.0018X**

Page 3 of 4

Date of issue: 2022-11-08

Issue No: 5

EQUIPMENT:

Equipment and systems covered by this Certificate are as follows:

The MTL SUM5 Universal Isolator is designed to provide a digital or analogue interface for equipment located in the hazardous area and repeat the signals in the non-hazardous area, whilst restricting the transfer of energy from unspecified non-hazardous area equipment to the intrinsically safe equipment by means of limitation of voltage and current.

The MTL SUM5 Universal Isolator comprises two interconnected modules; an Interface Module (MTL4-ADIO Universal Analogue / Digital Interface Module), and a Base Module, which can either be standard type (MTL4-BSIS IS Module Base) or relay output type (MTL4-BSISR IS Module Relay Base).

The Interface Module comprises an isolating transformer, opto-isolator circuits that provide galvanic isolation between the hazardous and non-hazardous area circuitry and zener diode / resistor arrangements providing voltage and current limitation. The above, together with other electronic components, are mounted on a single printed circuit board and housed in a moulded plastic enclosure. The internal connections between the Interface Module and associated Base Module are made via an edge-connect type plug and socket arrangement.

The Base Module provides the external hazardous area connection via four screw terminals along one side of the base with the non-hazardous area connections being made via a polarised plug connection at the bottom of the base designed to connect to an associated backplane. The Interface Module clips to the other side of the Base Module. In addition to providing the connection facilities, the Base Module also contains additional zener diode and current limiting resistor arrangements to provide further voltage and current limitation on the hazardous area side of the circuit. The Base Module is fitted with Loop Disconnect above the Interface Module that allows the hazardous area terminals to be isolated. The Base Module is also fitted with a RFID circuit to allow identification of the Isolator when fitted in a system. Two Base Module variants are available, the standard MTL4-BSIS IS Module Base and the MTL4-BSISR IS Module Relay Base.

The MTL4-BSIS IS Module Base is additionally fitted with an IS Power Jumper Link on the top edge of the module to allow the output current of the hazardous area outputs to be changed depending on the configuration of the isolator.

The MTL4-BSISR IS Module Relay Base provides a galvanically isolated SPDT relay contacts suitable for switching an intrinsically safe source of up to 30V. The relay contacts are rated 30V and 1A.

The MTL SUM5 Universal Isolator can optionally be fitted with Surge protection on the hazardous area connections by the fitting of a Plug-In Surge Module that plugs into the top of the Base Module. An earth screw connection facility is provided at the bottom of the Base Module to allow for connection to earth arrangement on the backplane required for surge protection. There are two variants of Plug-in Surge Module, the MTL4-SD Plug-In Surge Module designed to be fitted to the MTL4-BSIS IS Module Base, and the MTL4-SDR Plug-In Relay Surge Module designed to be fitted to the MTL4-BSISR IS Module Relay Base.

The configuration of the MTL SUM5 Universal Isolator as either an analogue input or output, or digital input or output, is dependent on the Interface module fitted, the position of the IS Power Jumper Link on the Base Module (where applicable) and the software configuration of the Interface Module fitted.

SPECIFIC CONDITIONS OF USE: YES as shown below:

1. The non-hazardous area connections of the equipment must be supplied from either safety extra low-voltage (SELV) or protective extra low-voltage (PELV) circuits; for example equipment complying with the requirements of either the IEC 60950 series, IEC 61010-1 or a technically equivalent standard.
2. When fitted with the optional surge modules the equipment is not capable of withstanding the 500V dielectric strength test required by clause 6.3.13 of EN 60079-11: 2012. This must be taken into account when installing the equipment.
3. MTL4-BSISR IS Module Relay Base only: The circuits connected to these modules are limited to overvoltage category I/II/III (non mains/ mains circuits) as defined in IEC 60664-1.



IECEX Certificate of Conformity

Certificate No.: **IECEX BAS 19.0018X**

Page 4 of 4

Date of issue: 2022-11-08

Issue No: 5

DETAILS OF CERTIFICATE CHANGES (for issues 1 and above)

Variation 5.1

To permit minor drawing changes not affecting the previous assessment.

ExTR: GB/BAS/ExTR22.0187/00	File Reference: 22/0280
------------------------------------	--------------------------------

Annex:

[IECEX BAS 19.0018X Annex Iss. 2.pdf](#)

<p>SGS Baseefa Limited Rockhead Business Park Staden lane, Buxton, Derbyshire SK17 9RZ United Kingdom</p>	
<p>ANNEX to IECEx BAS 19.0018X</p>	<p>Issue No. 2</p> <p>Date: 2021/03/12</p>

MTL SUM5 Universal Isolator
Input & Output Parameters – MTL4-BSIS IS Module Base & MTL4-ADIO Interface Module

Non-Hazardous Area Connector CON1, Pins 1 to 6 & 9 to 12

$$U_m = 30V$$

The non-hazardous Connector CON1, pins 1 to 6, & 9 to 12 are designed to operate from a d.c. supply voltage of up to 30V supplied from either safety extra low-voltage (SELV) or protective extra low-voltage circuits; for example equipment complying with the requirements of either the IEC 60950 series, IEC 61010-1 or a technically equivalent standard.

Digital O/P Configuration - Hazardous Area Terminals 4 w.r.t. 3 (IS Power Jumper Link not Fitted)

$$\begin{aligned} U_o &= 26.5V & C_i &= 0 \\ I_o &= 90mA & L_i &= 0 \\ P_o &= 0.6W \end{aligned}$$

Digital O/P Configuration - Hazardous Area Terminals 4 w.r.t. 3 (IS Power Jumper Link Fitted)

$$\begin{aligned} U_o &= 26.5V & C_i &= 0 \\ I_o &= 136mA & L_i &= 0 \\ P_o &= 0.9W \end{aligned}$$

Analogue O/P Configuration – Hazardous Area Terminals 4 w.r.t. 2 (IS Power Jumper Link not Fitted)

$$\begin{aligned} U_o &= 26.5V & C_i &= 0.5nF \\ I_o &= 90mA & L_i &= 0 \\ P_o &= 0.6W \end{aligned}$$

Analogue O/P Configuration – Hazardous Area Terminals 4 w.r.t. 2 (IS Power Jumper Link Fitted)

$$\begin{aligned} U_o &= 26.5V & C_i &= 0.5nF \\ I_o &= 136mA & L_i &= 0 \\ P_o &= 0.9W \end{aligned}$$

Digital I/P Configuration – Hazardous Area Terminals 2 w.r.t. 3

$$\begin{aligned} U_o &= 10V & C_i &= 0.5nF \\ I_o &= 0.13mA & L_i &= 0 \\ P_o &= <1mW \end{aligned}$$

The hazardous area terminals 2 w.r.t. 3 are also considered suitable for the connection of an external intrinsically safe source with a $U_o = 30V$ and $I_o = 100mA$. When an intrinsically safe source is connected to these terminals the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous area terminals 1 & 4 must not be used when a source is connected to these terminals.

<p>SGS Baseefa Limited Rockhead Business Park Staden lane, Buxton, Derbyshire SK17 9RZ United Kingdom</p>	
<p>ANNEX to IECEx BAS 19.0018X</p>	<p>Issue No. 2</p> <p>Date: 2021/03/12</p>

Digital I/P Configuration – Hazardous Area Terminals 1 w.r.t. 2

$$\begin{array}{ll} U_o = 10V & C_i = 0.5nF \\ I_o = 14mA & L_i = 0 \\ P_o = 35mW \end{array}$$

Analogue I/P Configuration – Hazardous Area Terminals 2 w.r.t. 3

$$\begin{array}{ll} U_o = 10V & C_i = 0.5nF \\ I_o = 0.13mA & L_i = 0 \\ P_o = <1mW \end{array}$$

The hazardous area terminals 2 w.r.t. 3 are also considered suitable for the connection of an external intrinsically safe source with a $U_o = 30V$ and $I_o = 100mA$. When an intrinsically safe source is connected to these terminals the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source.

Hazardous area terminals 1 & 4 must not be used when a source is connected to these terminals.

Analogue I/P Configuration – Hazardous Area Terminals 4 w.r.t 2 (IS Power Jumper Link not Fitted)

$$\begin{array}{ll} U_o = 26.5V & C_i = 0.5nF \\ I_o = 90mA & L_i = 0 \\ P_o = 0.6W \end{array}$$

Analogue I/P Configuration – Hazardous Area Terminals 4 w.r.t 2 (IS Power Jumper Link Fitted)

$$\begin{array}{ll} U_o = 26.5V & C_i = 0.5nF \\ I_o = 136mA & L_i = 0 \\ P_o = 0.9W \end{array}$$

Analogue I/P Configuration – Hazardous Area Terminals 2 & 4 w.r.t 3 (IS Power Jumper Link not Fitted)

$$\begin{array}{ll} U_o = 26.5V & C_i = 0.5nF \\ I_o = 90mA & L_i = 0 \\ P_o = 0.6W \end{array}$$

Analogue I/P Configuration – Hazardous Area Terminals 2 & 4 w.r.t 3 (IS Power Jumper Link Fitted)

$$\begin{array}{ll} U_o = 26.5V & C_i = 0.5nF \\ I_o = 136mA & L_i = 0 \\ P_o = 0.9W \end{array}$$

SGS Baseefa Limited Rockhead Business Park Staden lane, Buxton, Derbyshire SK17 9RZ United Kingdom	
ANNEX to IECEx BAS 19.0018X	Issue No. 2
Date: 2021/03/12	

Load Parameters

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

GROUP	CAPACITANCE (μ F)	INDUCTANCE (mH)	OR L/R RATIO (μ H/ohm)
Hazardous Area Terminals 4 w.r.t. 3 (IS Power Jumper Link not Fitted)			
IIC	0.095	4.29	58
IIB*	0.73	17.1	235
IIA	2.45	34.3	471
I	4.3	56.3	774
Hazardous Area Terminals 4 w.r.t. 3 (IS Power Jumper Link Fitted)			
IIC	0.095	2.00	39
IIB*	0.73	8.40	157
IIA	2.45	16.4	315
I	4.3	56.3	517
Hazardous Area Terminals 4 w.r.t. 2 (IS Power Jumper Link not Fitted)			
IIC	0.094	4.29	58
IIB*	0.72	17.1	235
IIA	2.44	34.3	471
I	4.29	56.3	774
Hazardous Area Terminals 4 w.r.t. 2 (IS Power Jumper Link Fitted)			
IIC	0.094	2.00	39
IIB*	0.72	8.40	157
IIA	2.44	16.4	315
I	4.29	56.3	517
Hazardous Area Terminals 2 w.r.t. 3			
IIC	3.0	1,000	109,401
IIB*	20.0	1,000	437,606
IIA	100	1,000	875,213
I	180	1,000	1,435,897
Hazardous Area Terminals 1 w.r.t. 2			
IIC	3.0	172.4	1,015
IIB*	20.0	656.4	4,063
IIA	100	1,000	8,126
I	180	1,000	13,333
Hazardous Area Terminals 2 & 4 w.r.t. 3 (IS Power Jumper Link not Fitted)			
IIC	0.094	4.29	58
IIB*	0.72	17.1	235
IIA	2.44	34.3	471
I	4.29	56.3	774
Hazardous Area Terminals 2 & 4 w.r.t. 3 (IS Power Jumper Link Fitted)			
IIC	0.094	2.00	39
IIB*	0.72	8.40	157
IIA	2.44	16.4	315
I	4.29	56.3	517

* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

<p>SGS Baseefa Limited Rockhead Business Park Staden lane, Buxton, Derbyshire SK17 9RZ United Kingdom</p>	
<p>ANNEX to IECEx BAS 19.0018X</p>	<p>Issue No. 2</p> <p>Date: 2021/03/12</p>

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
 - the total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value or
 - the total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
 - the total L_i of the external circuit (excluding the cable) is $\geq 1\%$ of the L_o value and
 - the total C_i of the external circuit (excluding the cable) is $\geq 1\%$ of the C_o value.

The reduced capacitance of the external circuit (including cable) shall not be greater than $1\mu\text{F}$ for Groups IIB, IIA & I and 600nF for Group IIC.

The values of L_o and C_o determined by this method shall not be exceeded by the sum of all of the L_i plus cable inductances in the circuit and the sum of all of the C_i plus cable capacitances respectively.

Input & Output Parameters – MTL4-BSISR IS Module Relay Base & MTL4-ADIO Interface Module

Non-Hazardous Area Connector CON1, Pins 1 to 6 & 9 to 12

$U_m = 30\text{V}$

The non-hazardous Connector CON1, pins 1 to 6, & 9 to 12 are designed to operate from a d.c. supply voltage of up to 30V supplied from either safety extra low-voltage (SELV) or protective extra low-voltage circuits; for example, equipment complying with the requirements of either the IEC 60950 series, IEC 61010-1 or a technically equivalent standard.

Relay Contact Connections - Hazardous Area Terminals 1 (NO), 2 (NC) & 3 (COM)

$U_i = 30\text{V}$	$U_o = 0$
$C_i = 0$	$I_o = 0$
$L_i = 0$	

The relay contacts are rated to maximum 30V and 1A.